HUNDURE

PXR-51 EM Reader

 \bigcirc




Features

- Supports 125 KHz-EM card.
- Reading distance is around 6-8 cm.
- Keypad function. When working with control panel, it provides swiping card,press card number by keypad or swiping card with PIN code to access.(PXR-51EWK)
- Wide operation temperature range. It can be installed in different arctic or tropical regions.
- Case sensor detection function.
- Watchdog function secures system free from halting.



Ordering Information



Specifications

| Model No. | PXR-51EW | PXR-51EWK |
|------------------------|----------------------------|------------------------|
| Read Format | EM (125 KHz) | |
| Read Range | 6-8 cm | |
| Comm. Interface | Wiegand | |
| Input Ports | Case Sensor x 1 | |
| Keypad | No | Yes, 12 Key(0-9, *, #) |
| LED Indicators | Power / Comm. | |
| Beep Tone | Buzzer | |
| Power Input | DC 12V / 1A | |
| Current Consumption | 200mA (max) | |
| Operating Temp. | -40°C~ 70°C / -40°F~ 158°F | |
| Relative Humidity | 20% ~ 80%(Non-condensing) | |
| Dimentions (LxWxH)(mm) | 112 x 77 x 21 | |